

Product Name :
Digital Trainer

Product Code :
EEN0050



Description :

Digital Trainer

Technical Specification :

Digital Trainer 1. Breadboard : Solderless Bread board with 1680 inter connected

Tie Points

2. Pulse Switches : 2 No's. Bounce free push buttons

3. Logic Switches : 8 logic level Switches in Dip type .

4. Power Supply : Fixed: +5V at 750 mA

5. Power Sockets : Logic Probe Power Supply Sockets

6. Logic Input : 8 LED buffered logic level indicators

7. Variable Clock : Fine adjustment of clock frequency.

Clock range selection L: 10 – 40 Hz, H : 1K – 20K Hz.

8. Jacks : 2mm to BNC Socket 2 No. 2mm to 4mm Socket 2 No.

9. Components Provided : ICs – 4001/1, 7400/3, 7402/1, 7404/1, 7408/1,

7432/1, 7476/2, 7486/1, 74126/1, Resistors 1/4W

±5% 230E/1, 10K/1, 39K/1, LED 5mm/1

10. Accessories : Mains cord, 2mm Red & Black patch cords 5 each and 2mm to 1mm Red & Black 5 each

11. Instruction manual : Strongly supported by detailed operating instructions.

12. Logic Probe Omega Type LP-002 With 2mm Banana Pin Qt.1 Provided

- Wiring of all types of experiments become simple and less time consuming.
- The unit is operative on 230V ±10% at 50Hz AC Mains.
- Weight : 3 Kg. (Approx.)
- Dimension : W 340 x H 110 x D 210

Electrical and Electronics

Website: www.electricalelectronicsindia.com, **Email:** export@electricalelectronicsindia.com

Address: 6148/6, Guru Nanak Marg, Ambala Cantt, Haryana, India, **Phone:** +91-0171-2643080, 2601773