

Product Name :
Stereo Tape Recorder Trainer**Product Code :**
Consumer0001**Description :**

Stereo Tape Recorder Trainer

Technical Specification :

Stereo Tape Recorder Trainer

- Compact design
- Fault creation and diagnosis
- 42 Test Points
- More than 15 faults can be demonstrated on this trainer

- No soldering and de-soldering is required to simulate faults
- The main IC's are provided on socket to provide a facility to check similar IC' and also to create the faults by inserting faulty IC's in the sockets
- Test points detail with typical voltage and wave forms are provided in the manual
- In built power supply
- Two identical mono channels clubbed together to obtain stereo effect through stereo head Both internal and external recording facility available
- Recording process understood through LED indicator present in equalization section
- 8P-2W R/P switch mechanism planed widely through 16 nos 1P-2W toggle switches
- Separate bass/treble section to understand the effect of low frequency as well as high frequency signal
- Technical Specifications:
 - Amplifier Type: Class B amplifier
 - Audio Power Output: 14 W (7 W × 2 channels)
 - Frequency Response: 100 Hz to 8 KHz
 - Tape Speed: 4.75 cm / sec
 - Erase Head: Fix magnet
 - RP Head: YBBT 62 (Stereo)
 - Mechanism: R X 39
 - Motor: CCW 12 V DC
 - Mechanism Control: Record, Play, Reverse, Forward, Stop, Pause
 - Recording Facility: Condenser Mic and EP socket for feeding external signal
 - PCB Size (mm): 260 × 230
 - No. of faults: 15
 - No. of Test point: 42
 - Power Supply: 220 V ±10 %, 50 Hz / 60 Hz on
 - request

- Power Consumption: 8.17 W (approx.)

Electrical and Electronics

Website: www.electricelectronicsindia.com, **Email:** export@electricalelectronicsindia.com

Address: 6148/6, Guru Nanak Marg, Ambala Cantt, Haryana, India, **Phone:** +91-0171-2643080, 2601773